

(J) BK SW : Hardware Suspend Mode Push Bottom Connector.

Pin#	Function
1-2 Short	Suspend.
1-2 Open	No Action.

(K) JP60 & JP61 ; Power Saving Devices.

JP60 : Action on Power Saving " Doze" Mode.

JP61 : Action on Power Saving " Suspend" Mode.

JUPPERS

(A) CPU Type Configuration. (refer Appendix A)

(1) INTEL 486 CPU

CPU Type	DX/DX2/DX4	486SX	P24D
JP1	Open	Open	Open
JP2	3-4	3-4	1-2
JP3	Open	Open	2-3
JP4	2-3	2-3	1-2
JP5	2-3	2-3	1-2
JP6	1-2	1-2	1-2
JP7	2-3	2-3	2-3
JP8	3-4	Open	3-4
JP9	1-2,3-4	2-3	1-2,3-4
JP10	3-4	3-4	1-2,3-4
JP11	4-5	4-5	4-5
JP12	Open	Open	Open
JP13	Open	Open	1-2
JP14	Open	Open	1-2
JP15	Note 1	Open	Open
JP16	1-2	1-2	1-2

Note 1. JP15 : For 486DX4 Clock Multiplier Selections only:

1-2 short -- 2.5 times the External Clock.

2-3 short -- 2 times the External Clock.

Open -- 3 times the External Clock.